

**Newtons4th Ltd**

VERSATILE TEST &amp; MEASUREMENT EQUIPMENT

## A Guide to the Analysis of Standby Power (EN50564:2011)

This application guide is intended to serve as a thorough overview of testing in accordance with EN50564:2011, we will offer an insight into the intricacies of the standard and what is required for compliance. We will explain how the requirements specified in EN50564:2011 (the replacement for IEC62301) apply to Energy Star and EU Standby Power directives.

### Overview - Why do we test standby Power?

The current market is competitive and consumers now expect highly efficient devices that offer sophistication in order that a product will consume very little power when not in use without the disconnect the device from the mains. This is a reasonable expectation as technology now exists with the ability to significantly reduce power consumption of products when they are in an idle state. Household devices connected to the mains EN50564 was created (which has superseded IEC62301) in order to address issues related to measurement of low power devices, the low power devices mentioned in the standard can be any household mains powered device consuming a few watts or less.

















### EN50564:2011 - Overview

Many people assume that EN50564:2011 specifies limits for products in standby power mode whilst connected to the mains, this is in fact not the case as EN50564:2011 specifies test procedure for power consumption equipment. It also offers guidance for specifying measurement equipment (in particular power analyzers) for such tests. The standard specifically covers

- Issues associated with power measurements of a few watts or less
- Describes the testing of products with a supply voltage between 100V and 250V AC, but may also apply to 3 phase equipment
- May be used in conjunction with other standards for measuring energy efficiency

We should consider this standard as the "guidance for low power measurement", actual limits are specified in other standards or regulation documentation such as Energy Star or EU directive

### Suggested Equipment Combinations

Measurement Compliance Requirement	Analyzer	Accessories (optional)	Software (Free Download)	Calibration (optional)
Energy Star IEC62301 EN50564:2011 Standby Power	 PPA5500 Precision Power Analyzer	 Universal Breakout Box	 Standby Power Software	 7949
Energy Star IEC62301 EN50564:2011 Standby Power	 PPA4500 Precision Power Analyzer	 Universal Breakout Box	 Standby Power Software	 7949
Energy Star IEC62301 EN50564:2011 Standby Power	 PPA1500 Compact Power Analyzer	 Universal Breakout Box	 Standby Power Software	 7949
Energy Star IEC62301 EN50564:2011 Standby Power	 PPA500 Precision Power Analyzer	 Universal Breakout Box	 Standby Power Software	 7949

## What are the limits for standby power consumption?

In the EU, the limits for standby power are detailed in EU regulation 1275/2008/IEC, we have presented the limits in the table below;

1275/2008/IEC Maximum Limits for Power Consumption		
Mode	Maximum Power Consumption before Jan 07 2010	Maximum Power Consumption after Jan 07 2010
Off Mode	1.00W	0.50W
Standby Without Display	1.00W	0.50W
Standby With Display	2.00W	1.00W

Table 1

This regulation specifically references IEC62301 as a standard to refer to (which has now been superseded by EN50564), this is common with many regulatory documents around the world as the recognised test standard for any low power measurement of household products connected to the mains.

## Energy Star Requirement's

The Energy Star® program separates different products into categories and specifies limits specific to that product category, various modes are specified depending upon the equipment under example, the table below indicates limits applied to PC Monitor Displays. Three modes are described in the document titled "Energy star® program requirements for displays". These are "On mode and Off mode"

Energy Star Limits for Power Consumption of PC Monitor Displays		
Mode	Maximum Power Consumption	Notes
On Mode	See Section 3.3.1 of <a href="#">Energy star program requirements for displays</a>	"On Power" consumption has varied limits depending upon screen size and pixel density
Sleep Mode	0.5W	Capabilities such as bridge networks allow for increased sleep mode power consumption
Off Mode	0.5W	A product need not have an "Off mode" to be eligible for qualification

Table 2

It is clear that the limits described in energy star are very similar to the EU regulation 1275/2008/IEC. Even so, reference to each respective document should clearly still be made as compliance not automatically imply compliance to the other.

## What dictates a mode as "Off" or "Standby" in EN50564?

To a user, the differences between "off" and "standby" can be quite subtle.

- Off Mode : This mode describes a condition in which the product does not provide any function other than the ability to react to a users action to "activate" or "turn on" the device using similar. For the product to enter any other mode the soft button must be pressed and no automatic "cycling" into other modes takes place. Note that in off mode an indication LED can be considered a function.
- Standby Mode : Standby mode is one which facilitates one or more of the following functions; Activation of other modes by remote switch (such as a remote control, internal sensor or Continuous function (such as time being displayed on screen, or screen savers)

Modes not considered as "standby" include the following;

- Network communication through network interfaces, this can include RS-232, LAN, USB etc.
- PC's (or other devices) with "Wake on LAN" capability
- Sleep Mode as defined in Energy Star which maintain network connectivity such as quick restart of PC hard disks
- Security alarm reactivation
- Amongst others

It is possible for a manufacturer to choose to design a product without a standby mode or an off mode, provided that the product has an operating mode meeting the power consumption requirements of the particular directive.

## Preparing for Analysis

Once the mode of the device is known, the test equipment can be prepared and EN50564 provides excellent guidance for the selection of such equipment. The N4L Power Analyzers are well suited for standby power testing for various reasons, as described below;

1. EN50564 describes the likelihood of current waveform crest factors exceeding CF10 (EN50564:2011 Annex B, section B.1.2), all N4L power Analyzers offer a guaranteed accuracy specification of CF20. Furthermore, N4L Power Analyzers will auto range up without clipping of a waveform up to CF20.
2. All N4L Power Analyzers offer true no gap analysis at very high sample rates (PPA500/1500 1Ms/s, PPA4500/5500 2Ms/s), this is a necessity for reliable measurement as standby power often exhibit non periodic current pulses. If the analyser employs gapped analysis techniques these pulses can be missed and incorrect power measurements are likely.

## Test Environment

EN50564:2011 provides guidance for the test environment when testing low power devices, table 3 below indicates some of the key conditions that should be met

General Conditions for Measurements of Low Power to EN50564:2011		
Area	Limits	Notes
Test Room	Airflow close to product of less than 0.5m/s, room temperature of 23°C±0.5°C	Airflow across product should be controlled, room temperature maintained with air conditioning system.
AC Power Source Single Phase	Voltage regulation of ±1%, Frequency stability of ±1%	Mains supplies will not provide sufficient stability, specialist Sources can be recommended by N4L application engineer
AC Power Source Three Phase	Voltage regulation of ±1%, Frequency stability of ±1%	Mains supplies will not provide sufficient stability, specialist Sources can be recommended by N4L application engineer
Artificial (Impedance) Networks	Some low quality AC power sources have high frequency harmonic distortion, in these cases an impedance of 50 Ω/50 μH or 50 Ω/50 μH + 5 Ω as defined in EN 55016-1-2 should be used.	Utilising a high quality low distortion AC Power Source eliminates the requirement for an Artificial (Impedance) Network.

Table 3

The Harmonic Distortion and crest factor Requirements for the AC Power Source are detailed in table 4 below;

AC Power Source Harmonic Distortion Requirements for testing to EN50564:2011		
Parameter	Limits	Notes
THD %	2%	THD is described in EN50564 Section 4.3.2 as “the root-mean-square (r.m.s.) summation of the individual components using the fundamental as 100 %”, by the N4L Analyzers proving compliance of the AC source
Voltage Waveform Crest Factor	1.34 ~ 1.49	This crest factor must be maintained at all times during the test, even under highly distorted loading, this is analysed by the N4L Analyzers proving compli

Table 4

Section 4.3.2 states that power supplies meeting IEC61000-3-2 are likely to meet the above requirements, ultimately analysis of the power source will determine its compliance to the standa

Power Measurement Uncertainty

Section 4.4.1 of EN50564 describes the measurement uncertainty permitted with respect to the power analysis equipment including any external shunts utilised in the test. The “Maximum C used to determine the maximum measurement uncertainty and is dependent upon the size and characteristics of the load.

Maximum Current Ratio (MCR) = Crest Factor (CF) / Power Factor (PF)

Where crest factor is a ratio of the peak current drawn by the product and the RMS current drawn by the product, the power factor is a ratio of the measured real power to the measured app

Relative Uncertainty of Measurement Equipment		
MCR Category	Watts	Permitted Relative Uncertainty introduced by Power Measurement Device
≤10	≥1W	≤2% at 95% confidence level
	<1W	≤0.02W at 95% confidence level
>10	≥1W	0.02 · [1+ (0.08 · {MCR – 10})]
	<1W	The greater of 0.02W or Upc*measured value (Watts)

Table 5

Upc = 0.02 · [1+ (0.08 · {MCR – 10})]

Example uncertainty calculation: 2.04W Power Consumption, MCR = 13

Upc = 0.02 · [1+ (0.08 · {13 – 10})] = 0.02 · [1+ (0.08 · {13 – 10})] = 0.0248%

The N4L Power Analyzer’s we recommend in the “Example Test configurations” section below all fully comply with the relative uncertainty requirements in table 5 above.

Power Measurement Frequency Response

The frequency response of the Power Analyzer is vitally important in order to obtain accurate measurements and is often overlooked even though EN50564 is very specific with regards to the for wideband performance. The reason for this is that the current waveform of a product when in a low power standby mode can have very high crest factors (in excess of CF10) and as such, frequency harmonic components can be significant. In fact, EN50564 is very specific and states that the Power Analyzer used in the tests must be capable of measuring a waveform up to 2k uncertainty less than or equal to the limits specified in section 4.4.1 of the standard. For clarity we have documented the requirements with respect to frequency response (against the specific various N4L Power Analyzers) in table 6 below.

Requirement With Respect to Frequency Response (EN50564 Section 4.4.2)			
AC / DC	Accuracy	Compliant N4L Power Analyzers	Notes
DC	Meet all specifications as per table 5 above	PPA500(20Arms & 30Arms Models), PPA1500(20Arms & 30Arms Models), PPA4500(10Arms & 30Arms Models), PPA5500(10Arms & 30Arms Models)	No requirement for current shunt
AC up to and including 2kHz	Meet all specifications as per table 5 above	PPA500(20Arms & 30Arms Models), PPA1500(20Arms & 30Arms Models), PPA4500(10Arms & 30Arms Models), PPA5500(10Arms & 30Arms Models)	No requirement for current shunt

Table 6

Note : The PPA55x1 can offer a fully compliant solution when used in conjunction with an N4L HF external current shunt or any compliant current measurement sensor, this offers the flexibility measurement up to 50Arms along with excellent low level sensitivity for low power standby measurements to EN50564.

Power Measurements – Sampling approaches

The type of measurement approach will depend upon the characteristics of the power consumption “mode” with respect to time. A “mode” is considered to be “persistent where the power level where there are several power levels that occur in a regular sequence for an indefinite period of time.” Section 5.3.1 of EN50564 states that “Sampling Method” is the preferred method for all modes described in table 2 of this article.

Measurement Methods detailed in EN50564:2011 Section 5.3.1	
Method	Description
Sampling Method	If the product under test has a varying power in a cyclic fashion, is unstable or for limited duration modes – the sampling method is the only permitted measurement
Average Reading Method	Where the power consumption is stable and the mode is stable, the average reading method is a valid measurement approach. This is performed by averaging the power over a set period and dividing by the time
Direct Meter Reading Method	When the power reading is stable and the mode is stable, by simply recording the instrument power reading

Table 7

All N4L Power Analyzers’ employ the “Sampling Method” for Analysis of standby power as this is the preferred method. The “Sampling method” provides the fastest test method when the method this method should always be used whenever there is doubt as to the stability of the mode or the behaviour of the product. The standard states that the recording of power, voltage, current and parameters shall be recorded at intervals not exceeding 1 second.

## Non Cyclic Measurements

When the power consumption of the product under test is “non-cyclic”, the average power is assessed as follows;

Non Cyclic Standby Power Measurement: EN50564:2011 Section 5.3.2	
	Notes
Test Duration	Not less than 15 minutes
Discard of data	Data from the first third of the test is always discarded, stability is determined from the second 2/3 of data
Establishment of Stability	≤1 Watt : Linear regression of the power readings for final 2/3 of the test is less than 10mW/hr
	>1 Watt : Linear regression of the power readings for the final 2/3 of the test is less than 1% of the input power/hr

Table 8

If after 15 minutes of testing the stability criteria specified in table 8 are not achieved, the test period is continuously extended until the stability criteria is achieved (in the final 2/3 of the test stability is not able to be achieved after 3 hours of testing, the raw data should be assessed in order to determine if there are any patterns in the power consumption of the device that could be used in order to satisfy the stability requirements. Once stability is achieved the results are taken and this is considered to be the average power consumed in the second two thirds of the test. If a mode is non-cyclic and of varying power, consumption shall be recorded for a long enough period so that the cumulative range of all data points in the final 2/3 of the test fall within a band of  $\pm 0.2$  such a “non-cyclic varying power” mode shall not be less than 60 minutes to allow sufficient averaging.

## Cyclic Measurements

A cyclic measurement is defined as “a regular sequence of power states that occur over several minutes or hours” in section 5.3.2 of EN50564:2011, the standard also states that a minimum of 10 complete cycles shall be assessed. A cyclic power consumption pattern could be that of a network enabled device that occasionally communicates with a network in a cyclic fashion.

Cyclic Standby Power Measurement: EN50564:2011 Section 5.3.2	
	Notes
Initial Energising	The product shall be energised for not less than 10 minutes prior to recording any data
Secondary Stabilisation	The product is then left energised for not less than 2 comparison periods, where a comparison period is not less than two “cycles” and not have a duration less than 10 minutes.
Averaging	Calculate the average power for each comparison period
Calculate Mid Point in Time	Calculate the mid point in time for each period in hours
Establishment of Stability	Stability is established where the power difference between the two comparison periods divided by the time difference of the mid-points of the comparison periods is less than a slope of less than;
	≤1 Watt : 10mW/hr
	>1 Watt : 1% of the measured input power per hour
If Stability is not reached	Additional cycles are added equally to each comparison period until above criteria is reached

Once stability is achieved, the power is determined as the average of the readings from both comparison periods. Where the cycles are not stable or are irregular, a minimum of 10 cycles are required in order to adequately characterise power consumption.

## Limited Duration Modes

A manufacturer may specifically state a product has modes of “limited duration”, in these cases the mode will be recorded for its entire duration. The results of such tests are reported as an average power consumption in Watt Hours (Wh) and its duration is indicated, a statement in the report indicating that the mode was of “limited duration” should be made. If a mode is of limited duration, the requirement for the product to be operated for a minimum period before the test (such as in the cyclic test). If a product exhibits several “limited duration modes” of differing power, each mode shall be recorded separately and documented accordingly.

## Average Reading and Direct Meter Reading Methods

The sampling method offers a more comprehensive test of a product in comparison to the average reading method and direct meter reading methods, N4L have therefore implemented the sampling method.

## Setting up the Test N4L: Standby Power Software and the Power Analyzer

In this example we are going to be testing PC Monitor Displays, in preparation we power on the analyzer (A PPA5530 in this case) and allow it to warm up for 30 minutes, simultaneously we connect the AC source (A low distortion IEC61000-3-2 compliant source in this case) at 230Vrms, 50Hz.

N4L Standby power software takes care of all of the above requirements automatically, it will set the minimum test period to 15 minutes, assess the final two thirds of the test whilst discarding. Further to this, the test period is automatically extended if stability cannot be achieved after 15 minutes up to a maximum test time of 3 hours.

N4L Standby Power Software presents the user with an ir interface. The Brand, Model, Serial number, Rated Voltage Frequency and Power are all inputted.

The test environment data is also entered along with auto the Measurement Instrument details.

The “test Mode” dialog is set to “Non cyclic modes” in order to analyse the power consumption characteristics of the PC Monitor. The test results will be analysing in our example tests.

The first product we tested was an ACER B223PW PC monitor. Its rated current was 1.2A and it was manufactured in 2011. EU directive 1275/2008/IEC Maximum Limits for Power Consumption for displays we are looking for a power consumption below 1W for desktop display in order to comply.

Current Energy Star limits for standby power consumption Monitor displays as described in this document state 0.5W consumption measured in accordance with IEC62301 Ed : EN50564 has replaced IEC62301 Ed 2.0 we can refer to the standard for measurement requirements.

The next step is to test the AC source for compliance in accordance with table 3 in this article and section 4.3 in EN50564:2011. We will be measuring THD, Crest Factor, Voltage regulation stability – all will be tested against the limits specified in EN50564



N4L

N4L Standby POWER - 62301 & 50564 - v1.0.1.1

N4L

Newtons4th Ltd

Newtons4th Ltd.

Standby POWER

Connected to PPA

Interface: LAN

Export To .xls

Test Details

Test Conditions

Test

Nominal Test Conditions

Voltage (Vrms)

228.316

Frequency (Hz)

49.9950

Thd (%)

0.06861

Measured Value

Lower Limit

0.00000

Upper Limit

2.00000

Test Result

PASS

Crest Factor

1.41335

1.34000

1.49000

PASS

Read Data

At this stage we recommend that the device under test be connected to the output of the AC source and set to standby. This will result in the initial tests of the AC source being carried out under test conditions and will be representative of the behaviour of the AC source during the test. There is little benefit in testing the device with zero load as the test results may not be representative of the on-load output waveform of the Power Source.

As we can see the Voltage Total Harmonic Distortion (THD) is only 0.06861% for the AC source in use, this is very good and indicates an excellent clean power supply waveform for reliable test results. The crest factor was also very good and almost a sinusoid.

The next step is to select the "Test" tab and hit the "Start" button, this will commence the test period (minimum of 15 minutes) and data is collected at 1 second intervals.

N4L

N4L Standby POWER - 62301 & 50564 - v1.0.1.1

N4L

Newtons4th Ltd

Newtons4th Ltd.

Standby POWER

Connected to PPA

Interface: LAN

Export To .xls

Test Details

Test Conditions

Test

Standby Power

Power (W)

0.80508

Present Reading

Min Reading

0.80323

Max Reading

0.80633

Test Result

STABLE

Crest Factor

1.41279

1.41254

1.41340

Average Power (W)

0.80498

Power Gradient (W/hr)

0.00000

Accumulated Power (Whr)

0.20125

Monitor

Vrms

228.264

Total Power Factor

0.10412

Supply Frequency (Hz)

50.0002

Arms

0.03387

Apparent Power (VA)

7.73207

Load Duty Cycle (Hz)

49.9999

Test - Automatic

Test Period

Mins.

00

Secs.

00

Run

Abort

Interval

1

Sec(s)

Elapsed Time

15 : 00

Test - Manual

Start

Stop

The user interface of N4L Standby Power software offers information useful to the test engineer. The accumulated power is continuously analysed and the power gradient (analyzed according to EN50564:2011) is continually updated. In this test the power consumption was very low after 15 minutes and a result of 0.00000 (zero decimal places) was displayed.

We can see that the power consumption was 0.80508 W; the maximum and minimum readings very close to this figure tell us that the consumption was indeed "non cyclic".



We can now export this data as an excel report.

6/8

## Reporting

EN50564:2011 is very specific with regards to reporting of standby power, N4L standby power software complies with all requirements specified in EN50564:2011. Example screen shots of the reports are illustrated below;

N4L - Standby Power Test Report - 62301 & 50564				
N4L Standby Power v1.0.1.1				
Test Details				
Device Under Test				
Brand	Acer			
Model	B223PW			
Serial No.	ETLP80C0041152673C4010			
Rated Voltage (Vrms)	110-240V			
Rated Current (Arms)	1.2A			
Rated Frequency (Hz)	50-60Hz			
Rated Power (W)	288W			
DUT Notes				
Test Environment				
Lab Name	N4L			
Location	Office			
Date	09/09/2014			
Time	15:24			
Temperature	21 Degrees			
Humidity	60%			
Test No.	1			
Test Notes				
Measurement Instrument				
Manufacturer	NEWTONS4TH			
Model	PPA5530			
Serial No.	165-00777			
Firmware Level	2.106			
Nominal Test Conditions				
Voltage (V)	228.316			
Frequency (Hz)	49.995			
	Measured Value	Lower Limit	Upper Limit	Test Result
Vthd (%)	0.0686059	0	2	PASS
Crest Factor	1.41335	1.34	1.49	PASS
Test Results				
Monitor				
Vrms	228.264			
Arms	0.0338733			
Total Power Factor	0.104122699			
Apparent Power (VA)	7.73207			
Supply Frequency (Hz)	50.0002			
Load Duty Cycle (Hz)	49.9999			
Elapsed Time (mm:ss)	15:00			
Standby Power				
	Measured Value	Lower Limit	Upper Limit	Test Result
Power (W)	0.805084	0.803229	0.806328	STABLE
Crest Factor	1.41279	1.41254	1.4134	PASS
Average Power (W)	0.80498			
Accumulated Power (W/hr)	0.201245779			
Measurement Mode	None Cyclic			
Power Gradient	5.00843E-07			PASS



Additionally, graphs detailing the Vrms, Arms, Accumulated Power and the data log are all exported to excel from the N4L Standby Power Software.

Results

Below we list the results of various PC monitors assessed for standby power consumption in accordance with EN50564:2011, all products performed well in the test with very stable and most power consumption.

Standby Mode Power Consumption for PC Monitor Displays		
Brand	Model	Standby Power Consumption
ACER	B223PW	0.80508
ACER	B223PW	0.81755
Samsung	S24C300H	0.33819
BENQ	ET37309	0.38240